

1. Убедитесь, что роутер подключен к электричеству, а сетевой кабель СКТВ подключен в WAN порт роутера.
2. Подключитесь к Wi-Fi сети роутера (Имя сети и пароль указаны на обратной стороне роутера) или подключите ПК кабелем, который идет в комплекте, от любого порта LAN
3. Откройте браузер и перейдите по адресу <http://192.168.0.1>
4. Введите логин и пароль для входа в настройки роутера.
Логин и пароль по умолчанию:
admin
admin
5. В левой части выбираем пункт "Internet Setup", а в открывшемся в центральной части окне выбираем "Manual Internet Connection Setup":

The screenshot shows the D-Link DIR-320 web interface. At the top, it displays "Product Page : DIR-320" and "Firmware Version : 1.21". The D-Link logo is prominently featured. Below the logo is a navigation bar with tabs for "DIR-320", "SETUP", "ADVANCED", "MAINTENANCE", "STATUS", and "HELP". The "SETUP" tab is active, and the "Internet Setup" option is selected in the left-hand menu. The main content area is titled "INTERNET CONNECTION" and contains the following sections:

- INTERNET CONNECTION:** A text block explaining that for first-time configuration, the Internet Connection Setup Wizard is recommended, while the Manual Internet Connection Setup button is for manual configuration.
- INTERNET CONNECTION SETUP WIZARD:** A section with a button labeled "Internet Connection Setup Wizard" and a note advising users to follow the Quick Installation Guide before launching the wizard.
- MANUAL INTERNET CONNECTION OPTIONS:** A section with a button labeled "Manual Internet Connection Setup" highlighted by a red rectangle, indicating the next step in the process.

On the right side of the interface, there is a "Helpful Hints.." section with two bullet points: one for new users recommending the wizard, and one for advanced users recommending manual setup.

- В разделе «INTERNET CONNECTION TYPE» в поле «My Internet Connection is» выбираем «Russia PPPoE (Dual Access)». Далее, ставим галочку рядом с «Dynamic PPPoE».
- В полях «User Name», «Password» и «Retype Password» введите «Имя пользователя» и «Пароль» из договора с компанией СКТВ, повторите «Пароль».
- Нажмите кнопку "Save Settings":

INTERNET CONNECTION TYPE

Choose the mode to be used by the router to connect to the Internet.

My Internet Connection is : Russia PPPoE (Dual Access) ▼

RUSSIA PPPOE (DUAL ACCESS)

Enter the information provided by your Internet Service Provider (ISP).

Dynamic PPPoE Static PPPoE

User Name : 12345-NIKS MPPE :

Password : ••••••••

Retype Password : ••••••••

Service Name : (optional)

IP Address :

MAC Address : - - - - - (optional) Clone MAC Address

Receive DNS from ISP Enter DNS Manually

Primary DNS Address :

Secondary DNS Address : (optional)

Maximum Idle Time : 5 Minutes

MTU : 1492

Connect mode select : Always ▼ New Schedule

Manual Connect-on demand

802.1x :

WAN PHYSICAL SETTING

Dynamic IP Static IP

IP Address :

Subnet Mask :

Gateway : (optional)

Primary DNS Address : (optional)

Secondary DNS Address : (optional)

Save Settings Don't Save Settings

- Выбираем пункт "Wireless Setup", а в открывшемся в центральной части окне выбираем "Manual Wireless Connection Setup":

The screenshot shows the D-Link DIR-320 web interface. At the top, there is a navigation bar with tabs for SETUP, ADVANCED, MAINTENANCE, STATUS, and HELP. The left sidebar contains a menu with options: Internet Setup, Wireless Setup (highlighted with a red box), LAN Setup, Printer Setup, Time and Date, Parental Control, and Logout. Below the menu, there is a status indicator for Internet (Offline) and a Reboot button. The main content area is titled "WIRELESS CONNECTION" and contains the following text:

There are 2 ways to setup your wireless connection. You can use the Wireless Connection Setup Wizard or you can manually configure the connection.

Please note that changes made in this section will also need to be duplicated on your wireless clients and PCs.

WIRELESS CONNECTION SETUP WIZARD

If you would like to utilize our easy to use Web-based Wizard to assist you in connecting your new D-Link Systems Wireless Router to the Internet, click on the button below.

[Wireless Connection Setup Wizard](#)

Note: Before launching the wizard, please make sure you have followed all steps outlined in the Quick Installation Guide included in the package.

MANUAL WIRELESS CONNECTION OPTIONS

If you would like to configure the Internet settings of your new D-Link Router manually, then click on the button below.

[Manual Wireless Connection Setup](#)

On the right side, there is a "Helpful Hints.." section with two bullet points:

- If you are new to wireless networking and have never configured a wireless router before, click on **Wireless Connection Setup Wizard** and the router will guide you through a few simple steps to get your wireless network up and running.
- If you consider yourself an advanced user and have configured a wireless router before, click **Manual Wireless Connection Setup** to input all the settings manually.

- В поле «Wireless Network Name» введите название вашей будущей беспроводной сети или оставьте без изменений. Поставьте галочку в поле «Enable Auto Channel Selection».
- В поле «Network Key» введите пароль вашей будущей беспроводной сети или оставьте без изменений (минимум 8 символов).
- Нажмите кнопку "Save Settings":

Internet Setup

Wireless Setup

LAN Setup

Printer Setup

Time and Date

Parental Control

Logout

Internet Offline

Reboot

WIRELESS NETWORK

Use this section to configure the wireless settings for your D-Link router. Please note that changes made in this section may also need to be duplicated on your wireless client.

To protect your privacy you can configure wireless security features. This device supports three wireless security modes including: WEP, WPA and WPA2.

Save Settings Don't Save Settings

WI-FI PROTECTED SETUP (ALSO CALLED WCN 2.0 IN WINDOWS VISTA)

Enable :

Current PIN : **26896250**

Generate New PIN Reset PIN to Default

Wi-Fi Protected Status : Enabled / Not Configured

Reset to Unconfigured

Add Wireless Device with WPS

WIRELESS NETWORK SETTINGS

Enable Wireless :

Wireless Network Name : (Also called the SSID)

Enable Auto Channel Selection :

Wireless Channel :

Transmission Rate : (Mbit/s)

WMM Enable : (Wireless QoS)

Enable Hidden Wireless : (Also called the SSID Broadcast)

WIRELESS SECURITY MODE

Security Mode :

WPA/WPA2

WPA/WPA2 requires stations to use high grade encryption and authentication.

Cipher Type :

PSK / EAP :

Network Key : x

(8~63 ASCII or 64 HEX)

Save Settings Don't Save Settings

Готово! Проверяйте подключение к интернету и подключайтесь к Wi-Fi!